

**Table Pursuant to KT-CT.3.5.7# (Option 1) – Individual Tree Designation**  
**(06/2008)**

<b><u>Harvest Unit</u></b>	<b><u>Designation</u></b>	<b><u>Description of Included Timber</u></b> <b><u>(see Definitions Below)</u></b>
6, 7, 18, 20, 22, 23, 28, 29, 30, 33, 34, 36, 37, 38, 41, 43, 46, 49, 53, 55, 57, 59, 60, 62, 63, and 64	ITM	<ul style="list-style-type: none"> <li>• Remove all trees marked with blue paint above and below stump height.</li> <li>• Do not cut any trees marked with orange paint above and below stump height.</li> </ul>
4, 31, 45, and 47	DXD	<ul style="list-style-type: none"> <li>• Remove all Ponderosa pine marked with blue paint above and below stump height.</li> <li>• Remove all live Lodgepole pine with a stump diameter of 6.4” to 26.3”</li> <li>• Remove all live White fir with a stump diameter of 6.5” to 27.9”</li> <li>• Remove all live unmarked Ponderosa pine with a stump diameter of 7.2” to 9.9” that are within 18 feet of a live unmarked Ponderosa pine with a larger stump.</li> <li>• Do not cut any trees marked with orange above and below stump height.</li> </ul>

<u>Harvest Unit</u>	<u>Designation</u>	<u>Description of Included Timber</u> <u>(see Definitions Below)</u>
44, 51, 54, 58	DXD	<ul style="list-style-type: none"> <li>• Remove all Ponderosa pine marked with blue paint above and below stump height.</li> <li>• Remove all live Lodgepole pine with a stump diameter of 6.4” to 26.3”</li> <li>• Remove all dead standing Lodgepole with a stump diameter of 6.4” plus</li> <li>• Remove all live White fir with a stump diameter of 6.5” to 27.9”</li> <li>• Remove all live unmarked Ponderosa pine with a stump diameter of 7.2” to 9.9” that are 18 feet or less from an unmarked live Ponderosa pine with a larger stump.</li> <li>• Do not cut any trees marked with orange above and below stump height.</li> </ul>
50 and 61	DXD	<ul style="list-style-type: none"> <li>• Remove all Ponderosa pine marked with blue paint above and below stump height.</li> <li>• Remove all live Lodgepole pine with a stump diameter of 6.4” to 26.3”</li> <li>• Remove all live White fir with a stump diameter of 6.5” to 27.9”</li> <li>• Remove all live unmarked Ponderosa pine with a stump diameter of 7.2” to 9.9” that are 18 feet or less from an unmarked live Ponderosa pine with a larger stump.</li> <li>• Remove all dead standing trees that are within 150 horizontal feet from the electric wire of a powerline</li> <li>• Do not cut any trees marked with orange above and below stump height.</li> </ul>

<u>Unit</u>	<u>Designation</u>	<u>Description of Included Timber</u> <u>(see Definitions Below)</u>
8, 9, 12, 13, 14, 19, 24, 26, 32, 39, 40, 48, and 52	DXD	<ul style="list-style-type: none"> <li>• Remove all live trees not marked orange paint above and below stump height, which meet the minimum tree diameter stated in AT.2</li> <li>• Remove all live unmarked Ponderosa pine with a stump diameter of 7.2' to 9.9" that are 18 feet or less from an orange marked tree, or a live unmarked Ponderosa pine with a larger stump diameter.</li> </ul>
1 and 27	DXD	<ul style="list-style-type: none"> <li>• Remove all live trees not marked orange paint above and below stump height, which meet the minimum tree diameter stated in AT.2</li> <li>• Remove all live unmarked Ponderosa pine with a stump diameter of 7.2' to 9.9" that are 18 feet or less from an orange marked tree, or a live unmarked Ponderosa pine with a larger stump diameter.</li> <li>• Remove all dead standing trees that are within 150 horizontal feet from the electric wire of a powerline</li> </ul>

<u>Unit</u>	<u>Designation</u>	<u>Description of Included Timber</u> <u>(see Definitions Below)</u>
3 and 5	DXD	<ul style="list-style-type: none"> <li>• Remove all live trees not marked orange paint above and below stump height, which meet the minimum tree diameter stated in AT2.</li> <li>• Remove all live unmarked Ponderosa pine with a stump diameter of 7.2' to 9.9" that are 18 feet or less from an orange marked tree, or a live unmarked Ponderosa pine with a larger stump diameter.</li> <li>• Remove all live Lodgepole pine with a stump diameter of 6.4" to 26.3"</li> <li>• Remove all dead standing Lodgepole with a stump diameter of 6.4" plus.</li> </ul>
2, 10, 11, 15, 16, 17, 21, 25, 35, 42, and 56	DXD	<ul style="list-style-type: none"> <li>• Remove all live Lodgepole pine with a stump diameter of 26.3" or less.</li> <li>• Remove all live White fir with a stump diameter of 27.9" or less.</li> <li>• Within a 30 foot radius (horizontal distance) around all Live Ponderosa pine with a stump diameter of 23.3" or greater, or any tree marked with Pink paint, leave the largest live Ponderosa pine stump diameter on a 10 foot minimum spacing.</li> <li>• Beyond the 30 foot radius, cut all live Ponderosa pine within 18 feet of a live Ponderosa pine with a larger stump diameter or an orange painted tree marked above and below stump height.</li> <li>• Ponderosa Pine with a stump diameter of 23.3" or greater shall not be included for harvest.</li> <li>• All blue marked Ponderosa pine above and below stump height regardless of spacing.</li> <li>• Do not cut any trees marked with orange above and below stump height.</li> </ul>

• Additional timber to be cut, if any will be designated for cutting in accordance with CT.3.7

**Timber Subject to Agreement:**

<u>Units</u>	<u>Description</u>
6, 7, 18, 20, 22, 23, 28, 29, 30, 33, 34, 36, 37, 38, 41, 43, 46, 49, 53, 55, 57, 59, 60, 62, 63, and 64	<ul style="list-style-type: none"> <li>• Remove all live White fir 5.0” to 6.9” d.b.h.</li> <li>• Remove all live Lodgepole pine 5.0” to 6.9” d.b.h.</li> <li>• Remove all live Ponderosa pine 5.0” to 6.9” d.b.h. 18 feet or less from a live unmarked tree with a larger d.b.h.</li> <li>• Landing slash piles as agreed.</li> </ul>

**Definitions:**

1. DXD: Designation by Description
2. DXD Stump Height: Measure outside bark at 4 inches above the natural forest floor on the uphill side of the tree.
3. DXD Diameter: Measured at the 4” stump height outside bark of the tree, as presented, with diameter tape that is perpendicular to the bole of the tree. Measure to the nearest tenth of an inch.
4. DXD Stump Spacing: Measured nearest face to nearest face slope distance at the 4.0 inch stump height. (This does not need to be measured on the uphill side of the tree.)